## **DATASHEET - BZMC3-A400**



Circuit-breaker, 3 p, 400A

Part no. BZMC3-A400 Catalog No. 158271 Alternate Catalog BZMC3-A400



Similar to illustration

## Design verification as per IEC/EN 61439

3			
Technical data for design verification			
Rated operational current for specified heat dissipation	In	Α	400
Equipment heat dissipation, current-dependent	P <sub>vid</sub>	W	40
IEC/EN 61439 design verification			
10.2 Strength of materials and parts			
10.2.2 Corrosion resistance			Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures			Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat			Meets the product standard's requirements.
10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects			Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation			Meets the product standard's requirements.
10.2.5 Lifting			Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact			Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions			Meets the product standard's requirements.
10.3 Degree of protection of ASSEMBLIES			Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances			Meets the product standard's requirements.
10.5 Protection against electric shock			Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components			Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections			Is the panel builder's responsibility.
10.8 Connections for external conductors			Is the panel builder's responsibility.
10.9 Insulation properties			
10.9.2 Power-frequency electric strength			Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage			Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material			Is the panel builder's responsibility.
10.10 Temperature rise			The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating			Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility			Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function			The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

## **Technical data ETIM 7.0**

Low-voltage industrial components (EG000017) / Power circuit-breaker for trafo/generator/installation protection (EC000228)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Circuit breaker for power transformer, generator and system protection (ecl@ss10.0.1-27-37-04-09 [AJZ716013])

protection (ecl@ss10.0.1-27-37-04-09 [AJZ716013])		
Rated permanent current lu	Α	400
Rated voltage	V	415 - 415
Rated short-circuit breaking capacity Icu at 400 V, 50 Hz	kA	36
Overload release current setting	А	0 - 0
Adjustment range short-term delayed short-circuit release	А	0 - 0
Adjustment range undelayed short-circuit release	Α	2600 - 3800
Integrated earth fault protection		No
Type of electrical connection of main circuit		Screw connection

Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally open contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact No With switched-off indicator No With under voltage release No Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated No		
DIN rail (top hat rail) mounting optional  Number of auxiliary contacts as normally closed contact  Number of auxiliary contacts as normally open contact  Number of auxiliary contacts as change-over contact  Number of auxiliary contacts as change-over contact  No  With switched-off indicator  With under voltage release  No  Number of poles  Position of connection for main current circuit  Type of control element  Complete device with protection unit  Motor drive integrated  No  No  No  No  No  No  No  No  No  N	Device construction	Built-in device fixed built-in technique
Number of auxiliary contacts as normally closed contact  Number of auxiliary contacts as normally open contact  Number of auxiliary contacts as change-over contact  Number of auxiliary contacts as change-over contact  No  With switched-off indicator  No  With under voltage release  No  No  Number of poles  Position of connection for main current circuit  Type of control element  Complete device with protection unit  Motor drive integrated  No  No	Suitable for DIN rail (top hat rail) mounting	No
Number of auxiliary contacts as normally open contact  Number of auxiliary contacts as change-over contact  No With switched-off indicator  With under voltage release  No Number of poles  Sa Position of connection for main current circuit  Type of control element  Complete device with protection unit  Motor drive integrated  O  No Number of poles  Rocker lever  No No	DIN rail (top hat rail) mounting optional	No
Number of auxiliary contacts as change-over contact  With switched-off indicator  No  With under voltage release  No  Number of poles  3  Position of connection for main current circuit  Type of control element  Complete device with protection unit  Motor drive integrated  O  No  No	Number of auxiliary contacts as normally closed contact	0
With switched-off indicator  With under voltage release  No  Number of poles  Position of connection for main current circuit  Type of control element  Complete device with protection unit  Motor drive integrated  No  No	Number of auxiliary contacts as normally open contact	0
With under voltage release  No Number of poles  3 Position of connection for main current circuit  Type of control element  Complete device with protection unit  Motor drive integrated  No  No	Number of auxiliary contacts as change-over contact	0
Number of poles  Position of connection for main current circuit  Type of control element  Complete device with protection unit  Motor drive integrated  3  Rocker lever  No	With switched-off indicator	No
Position of connection for main current circuit  Type of control element  Complete device with protection unit  Motor drive integrated  Front side  Rocker lever  No	With under voltage release	No
Type of control element  Complete device with protection unit  Motor drive integrated  Rocker lever  Yes  No	Number of poles	3
Complete device with protection unit  Yes  Motor drive integrated  No	Position of connection for main current circuit	Front side
Motor drive integrated No	Type of control element	Rocker lever
· ·	Complete device with protection unit	Yes
Motor drive optional No	Motor drive integrated	No
	Motor drive optional	No
Degree of protection (IP) IP20	Degree of protection (IP)	IP20