

## GU10 BULB SOCKET



GU10 bulb base features in 10 mm (pin center-to-center distance) 2-pin bayonet mount and operating under mains voltage rather than lower voltage. This porcelain lamp holder is specifically designed to work with GU10 bulbs of different light source. Our product is rated up to 250V at 2A, which will satisfy your various lighting demands.

With the 150mm long silicon covered cable and the pre-cut ends, these lamp holders are rather easy to fit into your existing hard wired system. The two holes in the middle have metal contacts integrated, which are used to connect with the GU10 bulbs, the other two holes are for affixing screws.

### INSTALLATION

Bulb fitting and replacing are fairly easy: insert the bulb and gently twist it clockwise to lock the bulb in position. To remove the bulb, you twist it counter clockwise.

### DIMENSIONS

<b>Base Dimension</b>	ø28 mm x 15 mm
<b>Wire Length</b>	125 mm
<b>Base Type</b>	GU10
<b>Max Voltage</b>	250V
<b>Max Current</b>	2A
<b>Weight (Kgs)</b>	0.158

### APPLICATION

For LED, CFL and halogen bulb with GU10 base

#### Safety Notice

To avoid electric shock and burn, turn off the power and let the bulb cool before wiring and changing the lamps.

All of the above information, including drawings, illustrations and graphic designs, reflects our present understanding and is to the best of our knowledge and belief correct reliable. Users, however, should independently evaluate the suitability of each product for the desired application. Under no circumstances does this constitute an assurance any particular quality or performance. Such an assurance is only provided in the context of our product specifications or explicit contractual arrangements. Our liability for products set forth our standard terms and conditions of sale

